

**TECHNICAL SUPPLEMENT****Simplex DMR - VHF & UHF Cheat Sheet 20210715**VHF Digital Simplex

01	144.8000MHz	VHF Digital Calling	144.8DCALL
02	144.7500MHz	VHF Hi Site D-Spot	144.75DSPOT
03	144.7000MHz	VHF Digital Working	144.7000sim
04	144.7125MHz	VHF Digital Working	144.7125sim
05	144.7250MHz	VHF Digital Working	144.7250sim
06	144.7375MHz	VHF Digital Working	144.7375sim
07	144.7625MHz	VHF Digital Working	144.7625sim
08	144.7750MHz	VHF Digital Working	144.7750sim
09	144.7875MHz	VHF Digital Working	144.7875sim
10	144.8125MHz	VHF Digital Working	144.8125sim
11	144.8250MHz	VHF Digital Working	144.8250sim
12	144.8375MHz	VHF Digital Working	144.8375sim
13	144.8500MHz	VHF Digital Working	144.8500sim
14	144.8625MHz	VHF Digital Working	144.8625sim
15	144.8750MHz	VHF Digital Working	144.8750sim
16	144.8875MHz	VHF Digital Working	144.8875sim
17	144.9000MHz	VHF TubbyHub	144.9THUB

UHF Digital Simplex

01	439.0250MHz	UHF D-Spot	438.025dSPOT
02	439.0500MHz	UHF D-Spot	439.050dSPOT
03	439.0750MHz	UHF D-Spot	439.075dSPOT
04	439.2250MHz	UHF D-Spot	439.225dSPOT
05	439.2500MHz	UHF D-Spot	439.250dSPOT
06	439.0375MHz	UHF DigWork	439.0375sim
07	439.0625MHz	UHF DigWork	439.0625sim
08	439.0875MHz	UHF DigWork	439.0875sim
09	439.1125MHz	UHF DigWork	439.1125sim
10	439.1375MHz	UHF DigWork	439.1375sim
11	439.1625MHz	UHF DigWork	439.1625sim
12	439.1875MHz	UHF DigWork	439.1875sim
13	439.2125MHz	UHF DigWork	439.2125sim
14	439.2575MHz	UHF DigWork	439.2575sim
15	439.2625MHz	UHF DigWork	439.2625sim
16	439.2000MHz	UHF DCALL	439.2DCALL

Simplex DMR point to point operations in Australia normally deploy –  
12.5kHz bandwidth, Colour Code 1, Talk Group 99, Time Slot 1.

The current Wireless Institute of Australia sponsored Co-operative Band Plan specifies the following –  
VHF – Digital Simplex (12.5kHz or 25kHz channel spacing) – 144.700 to 144.900MHz

specific usage – 144.800MHz Digital Narrowband Calling, 144.750MHz Digital High Site Hotspot

Note that the frequencies specified here permit all digital voice modes including P25, Fusion, D-Star and others.

VK DMR-MARC also specify using 145.325, 145.350, 145.375MHz for hotspots however these frequencies are mainly used by Echolink, IRLP and AllStarLink analogue internet gateways in the region not linked to a repeater.

UHF – FM and Digital Simplex (12.5kHz or 25kHz channel spacing) – 438.950 to 439.775MHz

specific usage – 438.950MHz WICEN, 439.000MHz National FM Voice Calling, 439.100MHz APRS,

439.175 AX25, 439.200MHz Digital Voice Calling, 439.400MHz ARDF Beacons,

439.125MHz Digital and Analog Gateways, 439.150MHz Digital and Analog Gateways

Note that the frequencies specified here permit all digital voice modes including P25, Fusion, D-Star and others.

VK DMR-MARC also specify using 439.125, 439.150MHz for hotspots however caution is needed to prevent interference with already established Echolink, IRLP and AllStarLink analogue internet gateways in the region .

**Simplex/Duplex DMR Example Settings**

Some examples of settings for Repeater and Hotspot access are given here. There are a large number of UHF DMR Repeaters in Australia, along with a lesser amount of VHF DMR Repeaters. The VHF example given here is for the VK4RSA VHF DMR Repeater near Sarina Central Queensland, the UHF example given here is for the VK4TCA UHF DMR Repeater on Brisbane Northside. The Hotspot example given here is for the portable TUBBYHUB. There are also a huge number of Talk Groups on both the DMR-MARC and Brandmeister systems, some examples are given here however many more can be found online.

VHF Example – Output 146.675 Input 146.025 Bandwidth 12.5kHz

UHF Example – Output 439.750 Input 434.750 Bandwidth 12.5kHz

Hotspot Example – 144.900 Simplex Bandwidth 12.5kHz

LOCAL	Color Code 1 Time Slot 2 Talk Group 9	VK DMR/Brandmeister Local Working via Repeater
StateLnkd	Color Code 1 Time Slot 2 Talk Group 8	VK DMR All State Linked Repeaters
VKAU	Color Code 1 Time Slot 2 Talk Group 505	VK DMR/Brandmeister All Australia Linked Repeaters
BMYSF	Color Code 1 Time Slot 2 Talk Group 50599	Brandmeister YSF Bridge
BMQLD	Color Code 1 Time Slot 2 Talk Group 5054	Brandmeister All VK4 Linked Repeaters
BMLocal	Color Code 1 Time Slot 2 Talk Group 1	Brandmeister Local Working via Repeater
VKNets	Color Code 1 Time Slot 1 Talk Group 5	VK DMR Nets and News
BMANZEL	Color Code 1 Time Slot 2 Talk Group 2353432	Brandmeister ANZEL News and SAREX
BMp25	Color Code 1 Time Slot 2 Talk Group 50525	Brandmeister P25 Bridge
BMWICEN	Color Code 1 Time Slot 2 Talk Group 50565	Brandmeister WICEN
BMHELP	Color Code 1 Time Slot 1 Talk Group 98	Brandmeister Hotspot Help
PARROT	Color Code 1 Time Slot 2 Talk Group 9990	VK DMR/Brandmeister Parrot Reflector for Testing
RptStat	Color Code 1 Time Slot 1 Talk Group 5000	VK DMR Local Repeater Status Report
DISC	Color Code 1 Time Slot 1 Talk Group 4000	VK DMR/Brandmeister Disconnect Last Connection

TECHNICAL SUPPLEMENT

